

Gigaset Puma (Good class A400/A400A)

"The ergonomic phone with an essential feature set"







USP:

Top ergonomic design, easy to dial, read and listen

a/b (analogue) Interface: Implementation: HA/PBX DECT, GAP Standards:

Configuration: connection of 1 external line

cordless telephone for up to 4 handsets System:

Sound quality

- o High Sound Performance (HSP™)
- Handsfree (best quality) speaking activated by illuminated Send/ handsfree-key and with adjustable volume (5 levels)
- Adjustable volume of handset sound (5 levels)
- Ringer melody with on/off function via * key (long press) 0
- Ringer melody output via handsfree speaker
- Ringer melodies with adjustable volume settings (5 levels) and on/off function via * key (long press)
- 20 selectable ringtones 0
- Advisory tone (for key confirmation and low battery)

Convenience - phoning essentials

Range

Indoor range: up to 50 meters 0 Outdoor range: up to 300 meters

Operation time

Talk time: up to 20 hours Standby time: up to 220 hours

Phonebook and dialing

- Phonebook for up to 80 names and numbers
- Name indication for: incoming calls, outgoing calls, missed calls list, redial list
- Dial preparation (input of phone numbers before connecting) with correction possibility
- Big dial font for improved readability
- Redialing of the 10 last different numbers, start via send
- User-programmable speed-dial shortcuts using keys 0, 2-9
- Dialing: DTMF, Pulse, Flash (programmable)

Key Benefits

- High quality, ergonomic keypad (metal dome technology) Easy handsfree talking in brilliant ${\sf HSP}^{\sf TM}$ sound quality
- Long talk time/standby time up to 20/220 hours
- Illuminated b/w 1,7" Display
- Phonebook for up to 80 names and numbers

Receiving Calls

- Caller indication displayed via CLIP and CNIP 1)
- Display and send key lighted
- Selectable ringer melodies
 - 20 standard melodies
 - 5 loudness levels + off + crescendo
- Ringer melody output
 - in handset
 - in AM base station
- Individual ringer melody for internal calls

Missed Calls

- Display and message key signaling missed calls
- Comfortable access to missed calls list by dedicated, message key
- List showing up to 25 missed calls saving calls with caller indication (CLIP / CNIP - base station required) and time 1)
- Direct dialing out of the missed calls list

General additional features

- Plug & Play (unpack, connect the phone and conduct a
- High quality, ergonomic keypad (metal dome technology)
- Alarm clock with
 - selectable ringer melody
 - clock synchronization using CLIP information (country specific feature) 1)
- Date and time functions are protected against power failure
- Base unit and charger wall mountable
- Internal antennas





Display and menu features

Display

- Illuminated graphical b/w display, 1,7 " (96 x 64 pixel)
- Display illumination: amber

Standby

Display of date and time (default setting)

In idle

- 0 Display of date and time
- Display of state of battery life and signal strength
- Soft keys for quick selection of functions

While conducting a call

Display of call duration in talk mode

Menu

- Convenient menu for easy use in up to 28 languages 0 (variable according to geographical region)
- Simple operation via icons and text based menu and soft keys

Keypad features

- New ergonomic keypad in high quality material (metal dome technology)
- Precise keypad with large keys
- 12 numeric keys plus 7 function keys
- 4 way Navikey O
- Illuminated keypad including navigation area
- Keypad illumination: amber
- Illuminated Send/hands free key (green LED) and dedicated illuminated message key (red LED)
- 0 Keypad protection on/off via # key (long press)
- Ringer tones on/off via * key
- Dedicated message key (red LED) O
- Flash key (R) with long press for pause (P)
- INT on left side of 4 way navigation key
- Mute on right side of 4 way navigation key

ECO DECT

- Up to 60% less energy consumption 2) thanks to an energy-saving power supply
- Reduction of transmitting power to almost zero when handset is docked (with only 1 registered handset)
- ECO Mode manual reduction of transmitting power by
- ECO Mode Plus 4) for 100% reduction of transmitting power of base station and all registered handsets
- Variable reduction of transmitting power according to distance between handset and base station

Accessories

- Gigaset Repeater
- Up to 4 Gigaset handsets

Features with more than one handset

- Free internal calls between handsets
- 2 calls simultaneously (1 external, 1 internal)
- Phonebook transfer between handsets
- Ringing assigned to all or selected handsets for internal calls
- Internal transfer of external calls to another handset with prior consultation call
- 3 party conference (1 external / 2 internal participants) via internal recall or barge in
- Collective ringing on incoming external calls

Answering machine features 5)

- Integrated answering machine with up to 25 minutes recording time
- Simple usage via handset and keypad on base station (illuminated play key and on/off key)
- User defined and predefined announcement (170 Sec.)
- Display of new messages on handset
- Announcement of date and time for each message by voice2)
- Recording time adjustable: unlimited, 1/2/3 minutes, unlimited
- Call acceptance adjustable: immediately, automatic, after 10, 18, 30 Sec.
- Live listening of messages via base station
- Call pick up function to answer calls during message recording
- Recordings have unlimited protection against power failure
- PIN-protected remote control of answering machine

Fixed net operator features

Support of provider features by use of Flash key, *key and





Technical data

Handset

0 Standby time: up to 220 hours Talk time: up to 20 hours

Battery: 2 x AAA (NiHM), 550 mAh Charging time: 8h in base, 6h in charger

Indoor range: up to 50 meters Outdoor range: up to 300 meters 0

Dimensions H x W x D / weight (incl. batteries) Handset: 153 mm x 48 mm x 27 mm / 112 g

Base Station AM Base Station

Power-saving 230 V switch-mode power supply

Charging cradle in base station

0 Wall mountable

Paging key on front of base station

Operation of AM through keys on AM base

Speaker for ringer output in answering machine base

Connection of 1 external line

Connection of up to 4 handsets

Dimensions H x W x D / weight Base station: 122 mm x 104 mm x 32 mm / 89 a

Answering machine base: 122 mm x 125 mm x 36 mm / 134 g

External charger (for Duos/Trios only)

Wall mountable

Dimensions H x W x D / weight

Charger: 75 mm x 71 mm x 27 mm / 33 g

Package contents

1 handset

1 base station

2 standard AAA batteries (NiHM), 550 mAh

1 battery cover

1 power supply unit

1 telephone cord 0

1 user manual 0

Other packages

System Duo

System Trio

System Quattro

Handset-Bundle

AM System

AM System Duo

AM System Trio

AM System Quattro

Color

o Black

Market Introduction

Market launch in August 2010 (Germany)

1) Dependent on country / network/ operator

2) Compared to the previous generation of Gigaset base stations

3) For all registered handsets - in comparison to when ECO Mode is not activated and to our conventional cordless phones

4) When handset is idle or charging and when all registered handsets support ECO Mode Plus

5) Only for AM version (A400A)

Author

Name: Thomas Winter GC PM PLM Org.: +49-89-722-35305 thomaswinter@gigaset.com E-Mail:

Copyright GC 2010

Reproduction of the content of this document in whole or part and/or its disclosure to a third party is strictly forbidden without the permission of its owner. Offenders are liable to pay for the damages. All rights reserved in the event of the grant of a patent or the registration of a utility model or

Manufactured by Gigaset Communications GmbH under trademark license of Siemens AG.